

color key shows on "circuits" layer

Bring to Theater DMX extension to move console to seating area Ladders and planks


The Odyssey

Northfield Arts Guild

Light Plot

7/26/19 Scale: 1/4"

B. Bjorklund Revision:



Instrument Summary and Info: The Odyssey 8/5/19

Light		
	Altman 360Q 6x9	4 / 4
E== == == == == == == == == == == == ==	Lycian ClubSpot	1/0
	Altman 65Q 6in Fresnel	22 / 0
	Altman 360Q 4.5 x 6	2/0
	ETC CE Source4 26deg	1/0
	ETC CE Source4 Jr 26deg	1/0
	ETC CE Source4 Jr 36deg	4 / 0
	ETC CE Source4 PAR MCM (WFL)	4 / 0
	ETC CE Source4 Zoom 25-50deg	9/0
	Altman Q-Lite (Actually LED lamps along side walls)	1 / 0
Typical		

Bring to Theater

Wrenches
Color
Patterns (6) Leaf Bkup
Altman PTN Holder (6)
DMX Extension
DMX CAT
Board for console table
and clamps
Goose Neck lamps for table
Power strip
AC cable
Expression Manual
White Gaff & Sharpee

Circuit/Dimmer 9 in Theater doesn't seem to function

House Light is a dual system. Between shows, plug to a wall dimmer. For show use, plug to circuit 12. Both are in the control balcony area. Patch circuit 12 to your favorite control channel on the console. House lights are LED lamps that don't fade well on the low end: (...

Color Summary

	•	
Color	Size	Count
L147	7.5"	3
L161	6.25"	1
L161	7.5"	2
L161	7.5in	7
NC	6.25"	2
R13	7.5in	6
R26	7.5in	2
R64	7.5in	2
R86	7.5in	2
R365	7.5"	3

