

The Maids		Wednesday, February 21, 2007			B. Bjorklund	
		Channel Hookup				
Channel	Circuit Number	Purpose	Color	Inst Type	Wattage	Unit Number
1	42B	A1b	R05x2	=65Q 6" Fres	750W	43
2	51A	A1a	R360/62	Alt 360Q 4.5 x 6	750W	31
3	49C	A1c	L162	=65Q 6" Fres	750W	53
5	48B	TopA1	R50	=65Q 6" Fres	750W	45
16	60	Bed Top	N/C	=65Q 6" Fres	750W	30
21	26B	A2b	R05x2	=65Q 6" Fres	750W	28
22	2B	A2a	R360/62	Alt 360Q 4.5 x 6	750W	16
23	33B	A2c	L162	=65Q 6" Fres	750W	47
25	32B	TopA2	R50	=65Q 6" Fres	750W	35
31	34A	A3b	R05x2	=65Q 6" Fres	750W	19
32	25A	A3a	R360/62	Alt 360Q 4.5 x 6	750W	8
33	18B	A3c	L162	=65Q 6" Fres	750W	39
35	40A	TopA3	R50	=65Q 6" Fres	750W	21
41	10B	A4b	R05x2	=65Q 6" Fres	750W	11
42	9A	A4a	R360/62	Alt 360Q 4.5 x 6	750W	3
43	1B	A4c	L162	=65Q 6" Fres	750W	25
45	16B	TopA4	R50	=65Q 6" Fres	750W	13
51	45B	A5b	R05x2	=65Q 6" Fres	750W	44
52	22B	A5a	R360/62	Alt 360Q 4.5 x 6	750W	33
53	38B	A5c	L162	=65Q 6" Fres	750W	54
55	35B	TopA5	R50	=65Q 6" Fres	750W	46
61	29B	A6B	R05x2	=65Q 6" Fres	750W	29
62	5B	A6a	R360/62	Alt 360Q 4.5 x 6	750W	17
63	36B	A6c	L162	=65Q 6" Fres	750W	48
65	19B	TopA6	R50	=65Q 6" Fres	750W	32
69	00	House Lt 1 (5 Fixtures)	N/C	TYPE 412	2000W	
70	00	House Lt 2 (6 fixtures)	N/C	TYPE 412	2000W	
71	37A	A7b	R05x2	=65Q 6" Fres	750W	20
72	28A	A7a	R360/62	Alt 360Q 4.5 x 6	750W	9
73	21B	A7c	L162	=65Q 6" Fres	750W	41
75	43A	TopA7	R50	=65Q 6" Fres	750W	22
81	13B	A8b	R05x2	=65Q 6" Fres	750W	12
82	12A	A8a	R360/62	Alt 360Q 4.5 x 6	750W	4
83	46A	A8c	L162	=65Q 6" Fres	750W	26
85	3B	TopA8	R50	=65Q 6" Fres	750W	14
91	27B	Vanity b	R05x2	=65Q 6" Fres	750W	36
92	20B	Vanity a	R360/62	Alt 360Q 4.5 x 6	750W	40

93	47B	Vanityc	L162	=65Q 6" Fres	750W	51
95	52A	VanityTop	R50	=65Q 6" Fres	750W	49
101	23	Bay b	R05x2	=65Q 6" Fres	750W	6
102	14A	Bay a	R360/62	Alt 360Q 4.5 x 6	750W	7
103	6B	Bay c	L162	=65Q 6" Fres	750W	23
105	4B	Bay Top	R50	=65Q 6" Fres	750W	10
111	41B	Ent b	R05x2	=65Q 6" Fres	750W	42
112	31B	Ent a	R360/62	Alt 360Q 4.5 x 6	750W	37
113	44B	Ent c	L162	=65Q 6" Fres	750W	50
120	50A	FL Ptn	N/C	SL50	575W	2
121	59	FL Ptn	N/C	SL50	575W	34
	59	FL Ptn	N/C	SL50	575W	24
122	66	FL Ptn	N/C	SL50	575W	52
123	11B	FL Ptn	N/C	SL50	575W	18
	11B	FL Ptn	N/C	SL50	575W	27
125	30A	Window Pattern	R362	SL50	575W	5
126	65	Back Light-Entrance	R57	SL50	575W	
127	56	WindowLt	R360/62			
	56	WindowLt	R360/62			
128	55	DoorBack	R360/62	SL50	575W	
130	7A	Aisle8:00	R360/62	=65Q 6" Fres	750W	1
131	15B	Aisle8:00	L162	=65Q 6" Fres	750W	15
140	17B	Aisle2:00	R05x2	=65Q 6" Fres	750W	38
141	39B	Aisle2:00	L162	=65Q 6" Fres	750W	55
145	58	Lamp		Practical		
146	64	Lamp	N/C	Practical		