

Controller Setup- Blood Brothers

| Blood Brothers |                |         | B Bjorklund    |                | Monday, November 5, 2007 |                 |
|----------------|----------------|---------|----------------|----------------|--------------------------|-----------------|
|                |                |         | Channel Hookup |                |                          |                 |
| Channel        | Circuit Number | Purpose | Color          | Position       | Unit Number              | Inst Type       |
|                |                |         |                | 1st Electric   | 20                       | Coloram II 7.5" |
|                |                |         |                | 1st Electric   | 17                       | Coloram II 7.5" |
|                |                |         |                | 1st Electric   | 13                       | Coloram II 7.5" |
|                |                |         |                | 2nd Electric   | 17                       | Coloram II 7.5" |
|                |                |         |                | 2nd Electric   | 12                       | Coloram II 7.5" |
|                |                |         |                | 2nd Electric   | 5                        | Coloram II 7.5" |
|                |                |         |                | 1st Electric   | 7                        | Coloram II 7.5" |
|                |                |         |                | Aux Elec Ln 10 | 10                       | Coloram II 7.5" |
|                |                |         |                | Aux Elec Ln 10 | 13                       | Coloram II 7.5" |
|                |                |         |                | Aux Elec Ln 10 | 16                       | Coloram II 7.5" |
|                |                |         |                | 1st Electric   | 4                        | Coloram II 7.5" |
|                |                |         |                | Aux Elec Ln 10 | 4                        | Coloram II 7.5" |
|                |                |         |                | Aux Elec Ln 10 | 7                        | Coloram II 7.5" |
| 1              | 60             | A1 F    | R119           | Rear Beam2     | 12                       | SL26            |
| 2              | 55             | A2 F    | R119           | Rear Beam2     | 10                       | SL26            |
| 3              | 51             | A3 F    | R119           | Rear Beam2     | 9                        | SL26            |
| 4              | 48             | A4 F    | R119           | Rear Beam2     | 7                        | SL26            |
| 5              | 43             | A5 F    | R119           | Rear Beam2     | 4                        | SL26            |
| 6              | 102            | A6 F    | R119           | Front Beam     | 16                       | SL26            |
| 7              | 97             | A7 F    | R119           | Front Beam     | 12                       | SL26            |
| 8              | 93             | A8 F    | R119           | Front Beam     | 10                       | SL26            |
| 9              | 90             | A9 F    | R119           | Front Beam     | 8                        | SL26            |
| 10             | 85             | A10 F   | R119           | Front Beam     | 4                        | SL26            |
| 11             | Q/26           | A11 F   | R119           | Apron Pipe     | 14                       | SL26            |
| 12             | M/27           | A12 F   | R119           | Apron Pipe     | 9                        | SL26            |
| 13             | G/21           | A13 F   | R119           | Apron Pipe     | 5                        | SL26            |
| 14             | 56             | AX F    | R119           | Rear Beam2     | 11                       | SL26            |
| 15             | 50             | AY F    | R119           | Rear Beam2     | 8                        | SL26            |
| 16             | 47             | AZ F    | R119           | Rear Beam2     | 6                        | SL26            |
| 21             | 119            | A1 CS T | Th Scroll      | 1st Electric   | 20                       | 65Q 6" Fres     |
| 22             | 124            | A2 CS T | Th Scroll      | 1st Electric   | 17                       | 65Q 6" Fres     |

Controller Setup- Blood Brothers

|    |       |              |           |                    |     |              |
|----|-------|--------------|-----------|--------------------|-----|--------------|
| 23 | 129   | A3 CS T      | Th Scroll | 1st Electric       | 13  | 65Q 6" Fres  |
| 24 | 133   | A4 CS T      | Th Scroll | 1st Electric       | 7   | 65Q 6" Fres  |
| 25 | 138   | A5 CS T      | Th Scroll | 1st Electric       | 4   | 65Q 6" Fres  |
| 26 | 206   | A6 CS T      | Th Scroll | Aux Elec Ln 10     | 16  | 65Q 6" Fres  |
| 27 | 209   | A7 CS T      | Th Scroll | Aux Elec Ln 10     | 13  | 65Q 6" Fres  |
| 28 | 257   | A8 CS T      | Th Scroll | Aux Elec Ln 10     | 10  | 65Q 6" Fres  |
| 29 | 253   | A9 CS T      | Th Scroll | Aux Elec Ln 10     | 7   | 65Q 6" Fres  |
| 30 | 220   | A10 CS T     | Th Scroll | Aux Elec Ln 10     | 4   | 65Q 6" Fres  |
| 31 | 150   | A11 CS T     | Th Scroll | 2nd Electric       | 17  | 65Q 6" Fres  |
| 32 | 153   | A12 CS T     | Th Scroll | 2nd Electric       | 12  | 65Q 6" Fres  |
| 33 | 158   | A13 CS T     | Th Scroll | 2nd Electric       | 5   | 65Q 6" Fres  |
| 34 | R/108 | AX Wm T      | R13       | Apron Pipe         | 15  | 65Q 6" Fres  |
| 35 | N/12  | AY Wm T      | R13       | Apron Pipe         | 10  | 65Q 6" Fres  |
| 36 | F/24  | AZ Wm T      | R13       | Apron Pipe         | 4   | 65Q 6" Fres  |
| 41 | 121   | A1 Cool T    | L161      | 1st Electric       | 19  | 65Q 6" Fres  |
| 42 | 125   | A2 Cool T    | L161      | 1st Electric       | 16  | 65Q 6" Fres  |
| 43 | 130   | A3 Cool T    | L161      | 1st Electric       | 11  | 65Q 6" Fres  |
| 44 | 135   | A4 Cool T    | L161      | 1st Electric       | 6   | 65Q 6" Fres  |
| 45 | 139   | A5 Cool T    | L161      | 1st Electric       | 3   | 65Q 6" Fres  |
| 46 | 207   | A6 Cool T    | L161      | Aux Elec Ln 10     | 15  | 65Q 6" Fres  |
| 47 | 210   | A7 Cool T    | L161      | Aux Elec Ln 10     | 12  | 65Q 6" Fres  |
| 48 | 256   | A8 Cool T    | L161      | Aux Elec Ln 10     | 9   | 65Q 6" Fres  |
| 49 | 254   | A9 Cool T    | L161      | Aux Elec Ln 10     | 6   | 65Q 6" Fres  |
| 50 | 219   | A10 Cool T   | L161      | Aux Elec Ln 10     | 3   | 65Q 6" Fres  |
| 51 | 151   | A11 Cool T   | L161      | 2nd Electric       | 16  | 65Q 6" Fres  |
| 52 | 154   | A12 Cool T   | L161      | 2nd Electric       | 11  | 65Q 6" Fres  |
| 53 | 159   | A13 Cool T   | L161      | 2nd Electric       | 4   | 65Q 6" Fres  |
| 54 | U/18  | AX C T       | L161      | Apron Pipe         | 13  | 65Q 6" Fres  |
| 55 | L/83  | AY Cool T    | L161      | Apron Pipe         | 8   | 65Q 6" Fres  |
| 56 | E/22  | AZ Cool T    | L161      | Apron Pipe         | 3   | 65Q 6" Fres  |
| 61 | P/20  | SideWarm A1  | R318      | Apron Pipe         | 11  | SL36         |
| 62 | J/23  | SideWarm A2  | R318      | Apron Pipe         | 6   | SL36         |
| 63 | C/11  | SideWarm A3  | R318      | Apron Pipe         | 2   | SL36         |
| 64 | BB/79 | SideWarm A4  | R318      | Apron Pipe         | 1   | SL36         |
| 65 | 25    | SideWarm A5  | R318      | Sidestage Right    | 1   | SL36         |
| 66 | 128   | SideWarm A6  | R318      | 1st Electric       | 14  | Alt 360Q 6x9 |
| 67 | 132   | SideWarm A7  | R318      | 1st Electric       | 8   | Alt 360Q 6x9 |
| 68 | 137   | SideWarm A8  | R318      | 1st Electric       | 5   | Alt 360Q 6x9 |
| 69 | 143   | SideWarm A9  | R318      | 1st Electric       | 1   | Alt 360Q 6x9 |
| 70 | 229   | SideWarm A10 | R318      | SL Proscenium Pipe | 137 | Alt 360Q 6x9 |

Controller Setup- Blood Brothers

|     |       |              |          |                    |    |              |
|-----|-------|--------------|----------|--------------------|----|--------------|
| 71  | 255   | SideWarm A11 | R318     | Aux Elec Ln 10     | 8  | Alt 360Q 6x9 |
| 72  | 221   | SideWarm A12 | R318     | Aux Elec Ln 10     | 5  | Alt 360Q 6x9 |
| 73  | 217   | SideWarm A13 | R318     | Aux Elec Ln 10     | 1  | Alt 360Q 6x9 |
| 74  | 44    | SideWarm AX  | R318     | Rear Beam2         | 5  | SL26         |
| 75  | 40    | SideWarm AY  | R318     | Rear Beam2         | 2  | SL26         |
| 76  | 37    | SideWarm AZ  | R318     | Rear Beam2         | 1  | SL26         |
| 81  | 19    | SideCool A1  | R57/L136 | Sidestage Left     | 1  | SL36         |
| 82  | 107   | SideCool A2  | R57/L136 | Apron Pipe         | 18 | SL36         |
| 83  | T/104 | SideCool A3  | R57/L136 | Apron Pipe         | 16 | SL36         |
| 84  | S/28  | SideCool A4  | R57/L136 | Apron Pipe         | 12 | SL36         |
| 85  | K/80  | SideCool A5  | R57/L136 | Apron Pipe         | 7  | SL36         |
| 86  | 215   | SideCool A6  | R57/L136 | SR Proscenium Pipe | 2  | Alt 360Q 6x9 |
| 87  | 118   | SideCool A7  | R57/L136 | 1st Electric       | 21 | Alt 360Q 6x9 |
| 88  | 122   | SideCool A8  | R57/L136 | 1st Electric       | 18 | Alt 360Q 6x9 |
| 89  | 126   | SideCool A9  | R57/L136 | 1st Electric       | 15 | Alt 360Q 6x9 |
| 90  | 131   | SideCool A10 | R57/L136 | 1st Electric       | 10 | Alt 360Q 6x9 |
| 91  | 205   | SideCool A11 | R57/L136 | Aux Elec Ln 10     | 18 | Alt 360Q 6x9 |
| 92  | 208   | SideCool A12 | R57/L136 | Aux Elec Ln 10     | 14 | Alt 360Q 6x9 |
| 93  | 258   | SideCool A13 | R57/L136 | Aux Elec Ln 10     | 11 | Alt 360Q 6x9 |
| 94  | 66    | SideCool AX  | R57/L136 | Rear Beam2         | 16 | SL26         |
| 95  | 65    | SideCool AY  | R57/L136 | Rear Beam2         | 15 | SL26         |
| 96  | 62    | SideCool AZ  | R57/L136 | Rear Beam2         | 13 | SL26         |
| 101 | 106   | PTNWsh W AB  | L147     | Front Beam         | 19 | SL36         |
| 102 | 101   | PTNWsh W AC  | L147     | Front Beam         | 15 | SL36         |
| 103 | 95    | PTNWsh W AD  | L147     | Front Beam         | 11 | SL36         |
| 104 | 103   | PTNWsh W AE  | L147     | Front Beam         | 17 | SL36         |
| 105 | 105   | PTNWsh W AF  | L147     | Front Beam         | 18 | SL36         |
| 106 | 100   | PTNWsh W AG  | L147     | Front Beam         | 14 | SL36         |
| 107 | 145   | PTNWsh W AH  | L147     | 2nd Electric       | 19 | SL50         |
| 108 | 148   | PTNWsh W AI  | L147     | 2nd Electric       | 15 | SL50         |
| 109 | 155   | PTNWsh W AJ  | L147     | 2nd Electric       | 8  | SL50         |
| 110 | 63    | PTNWsh W AA  | L147     | Rear Beam2         | 14 | SL36         |
| 111 | 91    | PTNWsh C AB  | R360/365 | Front Beam         | 9  | SL36         |
| 112 | 87    | PTNWsh C AC  | R360/365 | Front Beam         | 5  | SL36         |
| 113 | 81    | PTNWsh C AD  | R360/365 | Front Beam         | 1  | SL36         |
| 114 | 88    | PTNWsh C AE  | R360/365 | Front Beam         | 6  | SL36         |
| 115 | 82    | PTNWsh C AF  | R360/365 | Front Beam         | 2  | SL36         |
| 116 | 84    | PTNWsh C AG  | R360/365 | Front Beam         | 3  | SL36         |
| 117 | 149   | PTNWsh C AH  | R360/365 | 2nd Electric       | 13 | SL50         |
| 118 | 160   | PTNWsh C AI  | R360/365 | 2nd Electric       | 3  | SL50         |

Controller Setup- Blood Brothers

|     |      |               |          |                    |    |                       |
|-----|------|---------------|----------|--------------------|----|-----------------------|
| 119 | 162  | PTNWsh C AJ   | R360/365 | 2nd Electric       | 1  | SL50                  |
| 120 | 42   | PTNWsh C AA   | R360/365 | Rear Beam2         | 3  | SL36                  |
| 128 | 179  | Top AH        |          | 3rd Electric       | 3  | SL50                  |
| 129 | 190  | Top AI        |          | 3rd Electric       | 2  | SL50                  |
| 130 | 194  | Top AJ        |          | 3rd Electric       | 1  | SL50                  |
| 150 | 64   | CityHall4     |          | HL Bandbox 4       | 1  | Alt 360Q 6x12         |
| 151 | V/98 | GasStat7      |          | Apron Pipe         | 17 | SL50                  |
| 152 | 134  | BusStop       |          | 1st Electric       | 9  | SL50                  |
| 153 | 141  | UnPloyment16  |          | 1st Electric       | 2  | SL50                  |
| 154 | 218  | LyCityHouse19 |          | Aux Elec Ln 10     | 2  | SL50                  |
| 155 | 222  | FireScape20   |          | Aux Elec Ln 10     | 17 | SL50                  |
| 156 | 216  | LCountry22    |          | SR Proscenium Pipe | 1  | SL36                  |
| 157 | 156  | jail25        |          | 2nd Electric       | 6  | SL50                  |
| 158 | 147  | JohnCntry27   |          | 2nd Electric       | 18 | SL50                  |
| 159 | 161  | BoyGun26      |          | 2nd Electric       | 2  | SL50                  |
| 160 | 157  | Fair 28       |          | 2nd Electric       | 7  | SL50                  |
|     | 157  | Fair28        |          | 2nd Electric       | 14 | SL50                  |
| 161 | 146  | parking36     |          | 2nd Electric       | 10 | SL50                  |
| 162 | 152  | country38     |          | 2nd Electric       | 9  | SL50                  |
| 170 | 174  |               | Red      | 3rd Electric       | F3 | 3 Cell Sky Cyc Left   |
| 171 | 177  |               | Red      | 3rd Electric       | E3 | 3 Cell Sky Cyc Left   |
| 172 | 181  |               | Red      | 3rd Electric       | D3 | 3 Cell Sky Cyc Left   |
| 173 | 188  |               | Red      | 3rd Electric       | C3 | 3 Cell Sky Cyc Right  |
| 174 | 192  |               | Red      | 3rd Electric       | B3 | 3 Cell Sky Cyc Right  |
| 175 | 196  |               | Red      | 3rd Electric       | A3 | 3 Cell Sky Cyc Right  |
| 180 | 173  |               | Blue     | 3rd Electric       | F2 | 3 Cell Sky Cyc Center |
| 181 | 176  |               | Blue     | 3rd Electric       | E2 | 3 Cell Sky Cyc Center |
| 182 | 180  |               | Blue     | 3rd Electric       | D2 | 3 Cell Sky Cyc Center |
| 183 | 187  |               | Blue     | 3rd Electric       | C2 | 3 Cell Sky Cyc Center |
| 184 | 191  |               | Blue     | 3rd Electric       | B2 | 3 Cell Sky Cyc Center |
| 185 | 195  |               | Blue     | 3rd Electric       | A2 | 3 Cell Sky Cyc Center |
| 190 | 175  |               | Green    | 3rd Electric       | F1 | 3 Cell Sky Cyc Right  |
| 191 | 178  |               | Green    | 3rd Electric       | E1 | 3 Cell Sky Cyc Right  |
| 192 | 182  |               | Green    | 3rd Electric       | D1 | 3 Cell Sky Cyc Right  |
| 193 | 189  |               | Green    | 3rd Electric       | C1 | 3 Cell Sky Cyc Left   |
| 194 | 193  |               | Green    | 3rd Electric       | B1 | 3 Cell Sky Cyc Left   |
| 195 | 197  |               | Green    | 3rd Electric       | A1 | 3 Cell Sky Cyc Left   |
| 200 | 8    | Red Wash      | R26      | FS Booth Pipe HL   | 3  | SL26                  |
| 201 | 5    | Red Wash      | R26      | FS Booth Pipe HR   | 6  | SL26                  |
| 202 | 17   | Red Wash      | R26      | FS Booth Pipe HR   | 3  | SL26                  |

Controller Setup- Blood Brothers

|     |     |                    |     |                  |     |               |
|-----|-----|--------------------|-----|------------------|-----|---------------|
| 210 | 7   | Blue Wash          | R64 | FS Booth Pipe HL | 2   | SL26          |
| 211 | 4   | Blue Wash          | R64 | FS Booth Pipe HR | 5   | SL26          |
| 212 | 16  | Blue Wash          | R64 | FS Booth Pipe HR | 2   | SL 15/32      |
| 220 | 6   | Green Wash         | R92 | FS Booth Pipe HL | 1   | Alt 360Q 6x12 |
| 221 | 3   | Green Wash         | R92 | FS Booth Pipe HR | 4   | Alt 360Q 6x12 |
| 222 | 15  | Green Wash         | R92 | FS Booth Pipe HR | 1   | Alt 360Q 6x12 |
| 230 | 9   | UpLight AX         | N/C | Pit Floor        | 4   | SL50          |
| 231 | 10  | UpLight AY         | N/C | Pit Floor        | 3   | SL50          |
| 232 | 14  | UpLight AZ         | N/C | Pit Floor        | 1   | SL50          |
| 233 | 13  | UpLight AY RedWash | Red | Pit Floor        | 2   | SL50          |
| 250 | 282 | House Light Circ 3 |     | AudCeiling       | 2   | PAR 56 WFL    |
|     | 283 | House Light Circ4  |     | AudCeiling       | 1   | PAR 56 WFL    |
|     | 280 | House Light Circ 1 |     | AudCeiling       | 4   | PAR 56 WFL    |
|     | 281 | House Light Circ 2 |     | AudCeiling       | 3   | PAR 56 WFL    |
| 260 | 2   | Follow Spot        |     | HL FS Booth      | 26  | 1000Q         |
| 261 | 1   | Follow Spot        |     | HR FS Booth      | 112 | 1000Q         |
| 270 | 127 | Gobo Rotator       |     | 1st Electric     | 12  | SL50          |
| 271 | 99  | Special            | N/C | Front Beam       | 13  | SL19          |
| 272 | 89  | Special            | N/C | Front Beam       | 7   | SL19          |
|     |     |                    |     |                  |     |               |