

Channel	Circuit Number	Purpose	Color	Unit Number	Position	Inst Type
1	60	A1	R119	4	Rear Beam	Alt 360Q 6x12
2	57	A2	R119	7	Rear Beam	Alt 360Q 6x12
3	52	A3	R119	11	Rear Beam	Alt 360Q 6x12
4	47	A4	R119	14	Rear Beam	Alt 360Q 6x12
5	44	A5	R119	17	Rear Beam	Alt 360Q 6x12
6	59	A6	R119	5	Rear Beam	Alt 360Q 6x12
7	56	A7	R119	8	Rear Beam	Alt 360Q 6x12
8	51	A8	R119	12	Rear Beam	Alt 360Q 6x12
9	46	A9	R119	15	Rear Beam	Alt 360Q 6x12
10	43	A10	R119	18	Rear Beam	Alt 360Q 6x12
11	102	A11	R119	5	Front Beam	Alt 360Q 6x12
12	98	A12	R119	7	Front Beam	Alt 360Q 6x12
13	94	A13	R119	10	Front Beam	Alt 360Q 6x12
14	89	A14	R119	13	Front Beam	Alt 360Q 6x12
15	85	A15	R119	16	Front Beam	Alt 360Q 6x12
16	109	A16	R119	10	Apron	Alt 360Q 6x9
17	76	A17	R119	13	Apron	Alt 360Q 6x9
18	72	A18	R119	17	Apron	Alt 360Q 6x9
19	259	A19	R119	8	Aux Elec Line 11	Source 4 36deg
20	263	A20	R119	13	Aux Elec Line 11	Source 4 36deg
21	264	A21	R119	14	Aux Elec Line 11	Source 4 36deg
22	104	Aisle1	NC	4	Apron	Alt 360Q 6x9
	5	Aisle1	NC	1	BalconyLeft	Alt 360Q 6x9
23	67	Aisle2	NC	23	Apron	Alt 360Q 6x9
	8	Aisle2	NC	1	BalconyRt	Alt 360Q 6x9
31	103	A1T	NC	3	Apron	Alt 360Q 4.5 x 6
32	111	A2T	NC	8	Apron	Alt 360Q 4.5 x 6
33	78	A3T	NC	11	Apron	Alt 360Q 4.5 x 6
34	70	A4T	NC	19	Apron	Alt 360Q 4.5 x 6
35	34	A5T	NC	24	Apron	Alt 360Q 4.5 x 6
36	117	A6T	NC	3	First Elec	Alt 360Q 4.5 x 6
37	124	A7T	NC	7	First Elec	Alt 360Q 4.5 x 6
38	130	A8T	NC	11	First Elec	Alt 360Q 4.5 x 6
39	136	A9T	NC	16	First Elec	Alt 360Q 4.5 x 6
40	142	A10T	NC	20	First Elec	Alt 360Q 4.5 x 6

41	298	A11T	NC	2	Aux Elec Line 11	Alt 360Q 4.5 x 6
42	301	A12T	NC	6	Aux Elec Line 11	Alt 360Q 4.5 x 6
43	261	A13T	NC	10	Aux Elec Line 11	Alt 360Q 4.5 x 6
44	269	A14T	NC	16	Aux Elec Line 11	Alt 360Q 4.5 x 6
45	266	A15T	NC	19	Aux Elec Line 11	Alt 360Q 4.5 x 6
46	150	A16T	NC	4	Second Elec	Alt 360Q 4.5 x 6
47	155	A17T	NC	11	Second Elec	Alt 360Q 4.5 x 6
48	157	A18T	NC	16	Second Elec	Alt 360Q 4.5 x 6
49	11	A19T	NC	2	AuxElec 2	Alt 360Q 4.5 x 6
50	14	A20T	NC	5	AuxElec 2	Alt 360Q 4.5 x 6
51	18	A21T	NC	8	AuxElec 2	Alt 360Q 4.5 x 6
61	25 B	A1T	R368	2	Apron	65Q 6" Fres
62	112	A2T	R368	7	Apron	65Q 6" Fres
63	74	A3T	R368	15	Apron	65Q 6" Fres
64	71	A4T	R368	18	Apron	65Q 6" Fres
65	35	A5T	R368	22	Apron	65Q 6" Fres
66	116	A6T	R368	2	First Elec	65Q 6" Fres
67	121	A7T	R368	6	First Elec	65Q 6" Fres
68	126	A8T	R368	10	First Elec	65Q 6" Fres
69	135	A9T	R368	15	First Elec	65Q 6" Fres
70	141	A10T	R368	19	First Elec	65Q 6" Fres
71	297	A11T	R368	1	Aux Elec Line 11	65Q 6" Fres
72	300	A12T	R368	5	Aux Elec Line 11	65Q 6" Fres
73	260	A13T	R368	9	Aux Elec Line 11	65Q 6" Fres
74	270	A14T	R368	15	Aux Elec Line 11	65Q 6" Fres
75	267	A15T	R368	18	Aux Elec Line 11	65Q 6" Fres
76	147	A16T	R368	3	Second Elec	65Q 6" Fres
77	152	A17T	R368	10	Second Elec	65Q 6" Fres
78	159	A18T	R368	15	Second Elec	65Q 6" Fres
79	2	A19T	R368	1	AuxElec 2	65Q 6" Fres
80	16	A20T	R368	4	AuxElec 2	65Q 6" Fres
81	17	A21T	R368	7	AuxElec 2	65Q 6" Fres
91	66	PTNWmA	R13	1	Rear Beam	SL36
92	65	PTNWmB	R13	3	Rear Beam	SL36
93	58	PTNWmC	R13	6	Rear Beam	SL36
94	107	PTNWmD	R13	2	Front Beam	SL36
95	105	PTNWmE	R13	4	Front Beam	SL36
96	97	PTNWmF	R13	8	Front Beam	SL36
97	115	PTN WG	R13	1	First Elec	SL36
98	120	PTNWH	R13	5	First Elec	SL36
99	125	PTNWI	R13	9	First Elec	SL36
100	145	PTN WJ	R13	1	Second Elec	SL36
101	240	PTNWK	R13	4	Aux Elec Line 11	SL36
102	146	PTNWL	R13	6	Second Elec	SL36
111	45	PTNCoolA	R365	16	Rear Beam	SL36
112	41	PTNCoolB	R365	19	Rear Beam	SL36

113	37	PTNCoolC	R365	20	Rear Beam	SL36
114	90	PTNCoolD	R365	12	Front Beam	SL36
115	86	PTNCoolE	R365	15	Front Beam	SL36
116	80	PTNCoolF	R365	18	Front Beam	SL36
117	132	PTNCoolG	R365	13	First Elec	SL36
118	139	PTNCoolH	R365	18	First Elec	SL36
119	144	PTNCoolI	R365	22	First Elec	SL36
120	156	PTNCoolJ	R365	13	Second Elec	SL36
121	158	PTNCoolK	R365	18	Second Elec	SL36
122	161	PTNCoolL	R365	20	Second Elec	SL36
131	222	SideC	L344/R54	12	Stage Right Side Elec	SL26
132	210	SideC	L344/R54	14	Stage Right Side Elec	SL26
133	220	SideC	L344/R54	9	Stage Right Side Elec	SL 23/50
134	221	SideC	L344/R54	11	Stage Right Side Elec	SL26
135	217	SideC	L344/R54	5	Stage Right Side Elec	Source 4 36deg
136	218	SideC	L344/R54	6	Stage Right Side Elec	SL26
137	219	SideC	L344/R54	8	Stage Right Side Elec	SL26
138	208	SideC	L344/R54	1	Stage Right Side Elec	Source 4 36deg
139	207	SideC	L344/R54	3	Stage Right Side Elec	SL26
140	214	SideC	L344/R54	4	Stage Right Side Elec	SL26
141	26 F	SideC6.5	L344/R54	1	Apron	SL50
142	113	SideC8	L344/R54	6	Apron	SL50
143	75	SideC9.5	L344/R54	14	Apron	SL50
144	108	SideC1.5	L344/R54	1	Front Beam	SL36
145	106	SideC3	L344/R54	3	Front Beam	SL36
146	96	SideC4.5	L344/R54	9	Front Beam	SL36
151	246	SideWm	R08	14	Stage Left Side Elec	SL26
152	245	SideWm	R08	12	Stage Left Side Elec	SL26
153	244	SideWm	R08	11	Stage Left Side Elec	SL26
154	243	SideWm	R08	9	Stage Left Side Elec	SL 23/50
155	242	SideWm	R08	8	Stage Left Side Elec	SL26
156	241	SideWm	R08	6	Stage Left Side Elec	SL26
157	233	SideWm	R08	5	Stage Left Side Elec	Source 4 36deg
158	232	SideWm	R08	4	Stage Left Side Elec	SL26
159	231	SideWm	R08	3	Stage Left Side Elec	SL26
160	229	SideWm	R08	1	Stage Left Side Elec	Source 4 36deg
161	77	SideWm6.5	R08	12	Apron	SL50
162	36	SideWm8	R08	21	Apron	SL50
163	32	SideWm9.5	R08	26	Apron	SL50
164	91	SideWm1.5	R08	11	Front Beam	SL36
165	84	SideWm3	R08	17	Front Beam	SL36
166	79	SideWm4.5	R08	19	Front Beam	SL36
171	209	SideWash		13	Stage Right Side Elec	SL26
172	211	SideWash		10	Stage Right Side Elec	SL26
173	212	SideWash		7	Stage Right Side Elec	SL26
174	213	SideWash		2	Stage Right Side Elec	SL26

176	420				Stage Right Side Elec	The Scroller 7.5"
177	415				Stage Right Side Elec	The Scroller 7.5"
178	410				Stage Right Side Elec	The Scroller 7.5"
179	405				Stage Right Side Elec	The Scroller 7.5"
181	238	SideWash	Scroller	13	Stage Left Side Elec	SL26
182	235	SideWash	Scroller	10	Stage Left Side Elec	SL26
183	234	SideWash	Scroller	7	Stage Left Side Elec	SL26
184	230	SideWash	Scroller	2	Stage Left Side Elec	SL26
185	440				Stage Left Side Elec	The Scroller 7.5"
186	435				Stage Left Side Elec	The Scroller 7.5"
187	430				Stage Left Side Elec	The Scroller 7.5"
188	425				Stage Left Side Elec	The Scroller 7.5"
201	177	Red Cyc	R120	10	Third Elec	Cyc Unit
	181	Red Cyc	R120	16	Third Elec	Cyc Unit
	181	Red Cyc	R120	19	Third Elec	Cyc Unit
	174	Red Cyc	R120	1	Third Elec	Cyc Unit
	174	Red Cyc	R120	4	Third Elec	Cyc Unit
	177	Red Cyc	R120	7	Third Elec	Cyc Unit
	192	Red Cyc	R120	32	Third Elec	Cyc Unit
	188	Red Cyc	R120	28	Third Elec	Cyc Unit
	188	Red Cyc	R120	24	Third Elec	Cyc Unit
	196	Red Cyc	R120	43	Third Elec	Cyc Unit
	196	Red Cyc	R120	40	Third Elec	Cyc Unit
202	192	Red Cyc	R120	37	Third Elec	Cyc Unit
	176	Cyc Blue	R121	12	Third Elec	Cyc Unit
	180	Cyc Blue	R121	17	Third Elec	Cyc Unit
	180	Cyc Blue	R121	20	Third Elec	Cyc Unit
	173	Cyc Blue	R121	2	Third Elec	Cyc Unit
	173	Cyc Blue	R121	5	Third Elec	Cyc Unit
	176	Cyc Blue	R121	8	Third Elec	Cyc Unit
	191	Cyc Blue	R121	35	Third Elec	Cyc Unit
	187	Cyc Blue	R121	29	Third Elec	Cyc Unit
	187	Cyc Blue	R121	26	Third Elec	Cyc Unit
	195	Cyc Blue	R121	44	Third Elec	Cyc Unit
203	195	Cyc Blue	R121	41	Third Elec	Cyc Unit
	191	Cyc Blue	R121	38	Third Elec	Cyc Unit
	178	Cyc Green	R122	14	Third Elec	Cyc Unit
	182	Cyc Green	R122	18	Third Elec	Cyc Unit
	182	Cyc Green	R122	22	Third Elec	Cyc Unit
	175	Cyc Green	R122	3	Third Elec	Cyc Unit
	175	Cyc Green	R122	6	Third Elec	Cyc Unit
	178	Cyc Green	R122	9	Third Elec	Cyc Unit
	193	Cyc Green	R122	36	Third Elec	Cyc Unit
	189	Cyc Green	R122	30	Third Elec	Cyc Unit
189	Cyc Green	R122	27	Third Elec	Cyc Unit	
197	Cyc Green	R122	45	Third Elec	Cyc Unit	

	197	Cyc Green	R122	42	Third Elec	Cyc Unit
	193	Cyc Green	R122	39	Third Elec	Cyc Unit
211	19	Red	R120	1	FloorCycPosition	3 Cell Sky Cyc Right
	204	Red	R120	22	FloorCycPosition	3 Cell Sky Cyc Left
	19	Red	R120	4	FloorCycPosition	3 Cell Sky Cyc Right
	204	Red	R120	19	FloorCycPosition	3 Cell Sky Cyc Left
212	277	Red	R120	10	FloorCycPosition	3 Cell Sky Cyc Right
	277	Red	R120	13	FloorCycPosition	3 Cell Sky Cyc Right
213	29	Red	R120	16	FloorCycPosition	3 Cell Sky Cyc Left
	29	Red	R120	7	FloorCycPosition	3 Cell Sky Cyc Right
214	20	Blue	R121	2	FloorCycPosition	3 Cell Sky Cyc Center
	203	Blue	R121	23	FloorCycPosition	3 Cell Sky Cyc Center
	20	Blue	R121	5	FloorCycPosition	3 Cell Sky Cyc Center
	203	Blue	R121	20	FloorCycPosition	3 Cell Sky Cyc Center
215	278	Blue	R121	11	FloorCycPosition	3 Cell Sky Cyc Center
	278	Blue	R121	14	FloorCycPosition	3 Cell Sky Cyc Center
216	30	Blue	R121	17	FloorCycPosition	3 Cell Sky Cyc Center
	30	Blue	R121	8	FloorCycPosition	3 Cell Sky Cyc Center
217	24	Amber	R15	24	FloorCycPosition	3 Cell Sky Cyc Right
	24	Amber	R15	21	FloorCycPosition	3 Cell Sky Cyc Right
	21	Amber	R15	6	FloorCycPosition	3 Cell Sky Cyc Left
	21	Amber	R15	3	FloorCycPosition	3 Cell Sky Cyc Left
218	279	Amber	R15	12	FloorCycPosition	3 Cell Sky Cyc Left
	279	Amber	R15	15	FloorCycPosition	3 Cell Sky Cyc Left
219	23	Amber	R15	18	FloorCycPosition	3 Cell Sky Cyc Right
	23	Amber	R15	9	FloorCycPosition	3 Cell Sky Cyc Left
231	151	ScrimPtn	NC	7	Second Elec	SL50
	151	ScrimPtn	NC	14	Second Elec	SL50
	151	ScrimPtn	NC	9	Second Elec	SL50
232	149	ScrimPtn	NC	2	Second Elec	SL50
	160	ScrimPtn	NC	19	Second Elec	SL50
233	64	Window PTN		2	Rear Beam	SL26
234	54	Window PTN		9	Rear Beam	SL26
235	53	Bars PTN		10	Rear Beam	SL26
236	22	Ship Special	NC		Side Stage Left	SL19
	99	Ship Special	NC		Side Stage Right	SL19
261	114	A1T	R3411/3409	5	Apron	65Q 6" Fres
262	110	A2T	R3411/3409	9	Apron	65Q 6" Fres
263	73	A3T	R3411/3409	16	Apron	65Q 6" Fres
264	69	A4T	R3411/3409	20	Apron	65Q 6" Fres
265	31	A5T	R3411/3409	25	Apron	65Q 6" Fres
266	118	A6T	R3411/3409	4	First Elec	65Q 6" Fres
267	123	A7T	R3411/3409	8	First Elec	65Q 6" Fres
268	131	A8T	R3411/3409	12	First Elec	65Q 6" Fres
269	138	A9T	R3411/3409	17	First Elec	65Q 6" Fres
270	143	A10T	R3411/3409	21	First Elec	65Q 6" Fres

271	299	A11T	R3411/3409	3	Aux Elec Line 11	65Q 6" Fres
272	302	A12T	R3411/3409	7	Aux Elec Line 11	65Q 6" Fres
273	262	A13T	R3411/3409	12	Aux Elec Line 11	65Q 6" Fres
274	268	A14T	R3411/3409	17	Aux Elec Line 11	65Q 6" Fres
275	265	A15T	R3411/3409	20	Aux Elec Line 11	65Q 6" Fres
276	162	A16T	R3411/3409	5	Second Elec	65Q 6" Fres
277	153	A17T	R3411/3409	12	Second Elec	65Q 6" Fres
278	154	A18T	R3411/3409	17	Second Elec	65Q 6" Fres
279	12	A19T	R3411/3409	3	AuxElec 2	65Q 6" Fres
280	13	A20T	R3411/3409	6	AuxElec 2	65Q 6" Fres
281	15	A21T	R3411/3409	9	AuxElec 2	65Q 6" Fres
300	272	Fire	R15	11	Aux Elec Line 11	SL19
305					Aux Elec Line 11	
330	330	i-Cue			Front Beam	Accessory
	101		NC	6	Front Beam	SL19
335	335	i-Cue			Front Beam	Accessory
	88		NC	14	Front Beam	SL19
340	340	i-Cue			First Elec	Accessory
	133		NC	14	First Elec	SL26
345	345	i-Cue			Second Elec	Accessory
	148		NC	8	Second Elec	SL26
350	27	TreeLight		1	Left BandBox 1	Source 4 36deg
355	28	Tree Light		1	Right BandBox 1	Source 4 36deg
360	227	SideCPlat	L344	15	Stage Right Side Elec	SL26
361	240	SideWPlat	R08	15	Stage Left Side Elec	SL26
362	10	UpLight	R24	5	PitFloor	PAR16
	10	UpLight	R24	1	PitFloor	PAR16
	10	UpLight	R24	3	PitFloor	PAR16
363	9	UpLight	R15	6	PitFloor	PAR16
	9	UpLight	R15	4	PitFloor	PAR16
	9	UpLight	R15	2	PitFloor	PAR16
364	100	Musician	L344	1	Side Stage Right	SL50
375	228	Moon Image	Image Pro	1	BoomUpCenter	SL50
379	49	Trunk Sp	R365 w Iris	13	Rear Beam	SL19
400	282	House Circ 3	NA		House & Rehearsal Light	Soft Lite
	283	House Circ 1	NA		House & Rehearsal Light	Soft Lite
	280	House Circ 1	NA		House & Rehearsal Light	Soft Lite
	281	House Circ 2	NA		House & Rehearsal Light	Soft Lite
401	284	RearBeam Rehearsal			House & Rehearsal Light	Soft Lite
402	286	FrontBeam Rehearsal			House & Rehearsal Light	Soft Lite
403	285	Sidestage Left	NA		House & Rehearsal Light	Soft Lite
404	287	Sidestage R	NA		House & Rehearsal Light	Soft Lite
405	288	1st Elec	NA		House & Rehearsal Light	Soft Lite
406	289	2nd Elec	NA		House & Rehearsal Light	Soft Lite
407	290	3rd Elec	NA		House & Rehearsal Light	Soft Lite